

**Technical requirements for electronic control gears for LED and fluorescent luminaires (dimmable or non-dimmable) for operation on INOTEC central battery systems (CPS 220 / CPS FUSION) and emergency power supply systems (NEA)**

**- General requirements -**

|                                       |                                   |
|---------------------------------------|-----------------------------------|
| Manufacturer:                         | Type / Description:               |
| LEDVANCE GmbH                         | Luminaire                         |
| Parkring 1-5, 85748 Garching, Germany | EVG:                              |
|                                       | LED: LED TUBE T8 EM V 1200 mm 15W |
| Project / Place / Project ID:         | Specified by:                     |
|                                       | Name:                             |
|                                       | Company: LEDVANCE GmbH            |
|                                       | Date:                             |

| Features |                                                                       | Techn. data / INOTEC requirements                      | Explanation                                                                                                                                                 | Fullfilled (Yes / No) |
|----------|-----------------------------------------------------------------------|--------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------|
| 1        | Voltage range AC                                                      | 230V ± 10%                                             | Voltage range in normal mains operation                                                                                                                     | Yes                   |
| 2        | Voltage range DC                                                      | 186V - 260V                                            | Possible voltage range in emergency operation                                                                                                               | Yes                   |
| 3        | Control gear suitable for "Joker-Voltage" ?                           | B2-rectification of the AC voltage (without smoothing) | Pulsating DC voltage                                                     | Yes                   |
| 4        | Control gear compatible with change-over time of the system?          | Change-over time: 150 - 1000ms                         | Typical change-over time of INOTEC systems between mains- and battery operation                                                                             | Yes                   |
| 5        | Starting behavior of the control gear in AC and DC operation          | Stable current consumption within 1.6s                 | Necessary for individual lamp monitoring (SV). The nominal current of the control gear must be reached within this time if the lamp is intact or defective. | Yes                   |
| 6        | Control gear complies with the standard: (only for fluorescent lamps) | DIN EN 60929                                           | AC and/or DC-supplied electronic control gear for tubular fluorescent lamps - Performance requirements                                                      | Not relevant          |
| 7        | Control gear complies with the standard: (only for fluorescent lamps) | DIN EN 61347-2-3 (incl. Attachment J)                  | Particular requirements for AC and/or DC supplied electronic control gear for fluorescent lamps                                                             | Not relevant          |
| 8        | Control gear complies with the standard: (only for LED)               | DIN EN 62384                                           | DC or AC supplied electronic control gear for LED modules - Performance requirements                                                                        | Not relevant          |
| 9        | Control gear complies with the standard: (only for LED)               | DIN EN 61347-2-13                                      | Lamp control gear - Part 2-13: Particular requirements for DC or AC supplied electronic control gear for LED modules                                        | Yes                   |
| 10       | Control gear complies with the standard:                              | DIN EN 55015 (Measurement on AC and DC)                | Limits and methods of measurement of radio interference                                                                                                     | Yes                   |
| 11       | Control gear complies with the standard:                              | DIN EN 61000-3-2                                       | Electromagnetic compatibility (EMC) - Part 3-2: Limits - Limits for harmonic current emissions (equipment input current ≤ 16 A per phase)                   | Yes                   |
| 12       | Control gear complies with the standard:                              | DIN EN 61547                                           | Equipment for general lighting purposes — EMC immunity requirements                                                                                         | Yes                   |
| 13       | Control gear complies with the DALI-standards:                        | DIN EN 62386-101 / -102 / -207                         | The control and status information for monitoring the luminaire is provided via DALI commands. The DALI commands must be 100% compatible.                   | No                    |

Note: VDE 0108 is not a standard for ECG, marking is not applicable

**Technical requirements for electronic control gears for LED and fluorescent luminaires (dimmable or non-dimmable) for operation on INOTEC central battery systems (CPS 220 / CPS FUSION) and emergency power supply systems (NEA)**

**- Technical specifications -**

|                                       |                                   |
|---------------------------------------|-----------------------------------|
| Manufacturer:                         | Type / Description:               |
| LEDVANCE GmbH                         | Luminaire                         |
| Parkring 1-5, 85748 Garching, Germany | EVG:                              |
|                                       | LED: LED TUBE T8 EM V 1200 mm 15W |
| Project / Place / Project ID:         | Specified by:                     |
|                                       | Name:                             |
|                                       | Company: LEDVANCE GmbH            |
|                                       | Date:                             |

| Features |                                                                                                                                                                                                                 | Explanation                                                                                                                                                                                                                                                                                                                         | Manufacturer spec.                           |
|----------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------|
| 14       | Nominal current of the control gear with connected illuminant in <b>AC- operation (230V)</b>                                                                                                                    | Selection guide for the calculation of the max. number of luminaires per circuit                                                                                                                                                                                                                                                    | 78 mA                                        |
| 15       | Nominal current of the control gear with connected illuminant in <b>DC- operation (186V / 216V / 240V)</b>                                                                                                      | Selection guide for the calculation of the necessary battery capacity and selection guide for determination of the monitoring module to recognise a normal working lamp correctly.                                                                                                                                                  | 80 mA (186V)<br>69 mA (216V)<br>62 mA (240V) |
| 16       | Nominal current of the control gear with connected illuminant <b>at set dimming level</b> in <b>DC-operation (186V / 216V / 240V)</b> (for dimmable control gear)                                               | Selection guide for determination of the monitoring module to recognise a normal working lamp correctly.                                                                                                                                                                                                                            | - mA (186V)<br>- mA (216V)<br>- mA (240V)    |
| 17       | Current consumption of the control gear <b>without</b> or with <b>defective</b> illuminant in <b>DC- operation (186V and 240V)</b>                                                                              | Selection guide for determination of the monitoring module to recognise a lamp failure correctly.                                                                                                                                                                                                                                   | 12 mA (186V)<br>15 mA (240V)                 |
| 18       | Current consumption of the control gear <b>without</b> or with <b>defective</b> illuminant in <b>AC- operation (230V)</b>                                                                                       | Selection guide for determination of the monitoring module to recognise a lamp failure correctly.                                                                                                                                                                                                                                   | 10 mA                                        |
| 19       | Dimming level in emergency mode (DC or "Joker") (for dimmable control gear, if activated)                                                                                                                       | Important for the safety lighting design                                                                                                                                                                                                                                                                                            | 100 %                                        |
| 20       | DC detection <b>completely</b> deactivable ? (for dimmable control gear)                                                                                                                                        | To ensure correct operation, the control gear should not react to a change of the input voltage (DC or "Joker"). In this case, the INOTEC DALI module (DALI-SV module or FMD 230/DALI) controls the control gear.                                                                                                                   | Not relevant                                 |
| 21       | Max. inrush current of the control gear with connected illuminant in <b>AC- operation (230V)</b>                                                                                                                | Important for determining the maximum permissible number of luminaires per circuit in order to take account of the maximum contact load capacity of the circuit changeover circuit or monitoring module.                                                                                                                            | 6.8 A / $\mu$ s                              |
| 22       | Use of DALI commands according to IEC 62386 part 102:<br>- DPAC (level)<br>- RECALL MAX LEVEL 0x05<br>- RECALL MIN LEVEL 0x06<br>- QUERY STATUS 0x90<br>- QUERY ACTUAL LEVEL 0xA0<br>- QUERY LAMP POWER ON 0x93 | Control and status information for monitoring the luminaires:<br>- Direct setting of a dimming value<br>- Set maximum level<br>- Set minimum level<br>- Requests status telegram<br>- Requests current dimming value<br>- Requests status whether lamp is switched on<br>(after 2 / 2.5 / 3 seconds and cyclically every 3 seconds) | Not relevant                                 |

Luminaires, which should work as emergency lighting, have to be in accordance with DIN EN 60598-2-22. (Particular requirements - Luminaires for emergency lighting).

Notes:

For the correctness:

Place, Date

Stand: Apr. 2021

Signature